## Completely pre-assembled Signal Towers / KOMPAKT 37 K37 plug EM 24VAC/DC BU/WH/GN/YE/RD



ļ

Part No.:	698.260.75		
Series:	Kompakt 37		
MECHANICAL DATA			
Height		243 mm	
Diameter		38 mm	
Materials		PC	
Dome colour		Blue Clear Green Red Yellow	
Housing colour		Black	
Protection category		IP65	
Connection		M12 plug 8-pole	
Cable entry		Membrane grommet	
Cable entry minimum		d = 1 mm	
Cable entry maximum		d = 9 mm	
Tension relief		Pull-out protection	
Type of fixing		Built-in mounting	
Working te	mperature minim	um -20°C	
Working temperature maximum		um +50°C	
Weight with packaging		170 g	
Product weight		116 g	
ELECTRICAL DATA			
Operating voltage		24V	
Operating voltage type		AC/DC	
Operating voltage frequency		50Hz	
Operating voltage tolerance		+/- 10%	
Rated operational voltage		24 VDC	
Rated operational current		175 mA	
Rated inrush current		500 mA	
Protection class		Protection class 2	
Pollution degree		3 In the connection area: 2	
OPTICAL I	DATA		
Light source		LED	
Light colour		Blue Green Red White Yellow	


For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.

## Completely pre-assembled Signal Towers / KOMPAKT 37 K37 plug EM 24VAC/DC BU/WH/GN/YE/RD

Optical signal image	Permanent
Service life optical	50,000 h maximum
APPROVAL DATA	
Conforms with CE	Yes
Conforms with RoHS directive	Yes
WEEE	Yes
Conforms with ATEX-directive	No
Conforms with CCC	No
Conforms with UL	cULus
UL Type Rating	Туре 12 Туре 4Х
Conforms with FCC	No
Conforms with IC	No
EAC certificate available	Yes
Conforms with UKCA (Importer)	Yes (WERMA (UK) Ltd.)
Conforms with AS-I	No
ICAO Certification	No
Conforms with DNV	No
Conforms with RoHS CN	No
Conforms with VdS	No

Provide the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.

Completely pre-assembled Signal Towers / KOMPAKT 37 K37 plug EM 24VAC/DC BU/WH/GN/YE/RD



Provide the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.